

Socket outlets and special modular supports



0 042 80



0 042 85



4 129 50



4 129 50 + 0 775 94



4 129 50 + 4 129 51
+ 0 238 74



4 129 50 + 4 129 52



Dimensions [see e-catalogue](#)

Allow insertion of supply busbars

Pack	Cat.Nos	10-16 A - 250 V~	
10	0 042 80	Automatic terminals French standard 2P + $\perp$ shuttered	Number of modules 2.5
10	0 042 85	German standard 2P + $\perp$ shuttered	2.5
5	0 042 91	20 A - 400 V~ French standard 3P + $\perp$ shuttered	Number of modules 3.5
5	0 042 92	3P + N + $\perp$ shuttered	3.5
10	4 129 50	Special supports Modular support for rail Can be equipped with: - Arteor or Mosaic Programme 2-module mechanisms - Osmoz control and signalling units with the special adaptor Cat.No 4 129 51 - other equipment when used with the blanking plate Cat.No 4 129 52	Number of modules 2.5
10	4 129 51	Osmoz adaptor Pre-drilled adaptor for mounting Ø 22.5 mm control and signalling units on the modular support Cat.No 4 129 50	
10	4 129 52	Blanking plate Can be used as a blanking plate or for mounting different equipment on the modular support Cat.No 4 129 50 (e.g switches, lamps, printed circuits, potentiometers)	

Transformers, buzzers and bells



4 130 91



4 130 98



0 041 07



Dimensions [see e-catalogue](#)

Pack	Cat.Nos	Bell transformers						
		△ Conform to IEC / EN 61558-2-8 Protected against overloads and short circuits. In the event of an overload, switch "OFF" the power supply and allow the transformer to cool down before switching on again With label holders Wall or rail  mounting (for 4 modules) Possibility for supply busbars to run through (Cat.No 4 130 91)						
		230 V/12 V - 8 V						
		Secondary (V)	Rating (A)	Power (VA)	Number of modules			
1	4 130 91	12/8	0.66/1	8	2			
1	4 130 92	12/8	2/3	24	4			
		230 V/24 V - 12 V						
1	4 130 93	24/12	1/1.5	24 - 18	4			
		Safety transformers						
		Conform to IEC / EN 61558-2-6 Protected against overloads and short circuits. In the event of an overload, switch "OFF" the power supply and allow the transformer to cool down before switching on again Wall or rail  mounting (for 4 modules)						
		230 V/12 or 24 V						
		(per coupling 2 x 12 V for Cat.No 4 130 98)						
		Supplied with strip						
		P (VA)	No-load loss (W)	Voltage drop % Cos φ = 1	Efficiency % Cos φ = 1	Ucc (%)	I (A) primary loaded	Number of modules
1	4 130 96	25	2.5	29	66	23.3	0.142	5
1	4 130 98	63	4	15.7	75	13.6	0.33	5
		Buzzers and bells						
		50 Hz AC - Connection by screw terminals, with label holder Allow insertion of supply busbars Caution: remove lamps from illuminated push-buttons when used with Cat.Nos 0 041 01						
		Bells						
		Voltage (V~)	Power (VA)	Consum. (mA)	Acoustic power ¹ (dB)	Number of modules		
10	0 041 01	8/12	4/5	360/420	80/84	1		
10	0 041 07	230	6	27	83	1		
		Buzzers						
10	0 041 13	230	6	27	73	1		

1: Acoustic power at 1 m



Wiring management
accessories **p. 73**