

TECHNICAL DATA

Fluke 2052 Advanced Wire Tracer Kit







Key features

- Locate energized and de-energized wires quickly and accurately in walls, ceilings, and floors
- Find breaks or opens and shorts, and identify breakers and fuses easily
- CAT IV 600 V safety rated
- Includes the i400 AC Current Clamp accessory for inducing a tracing signal on the cable when there is no access to bare conductors

Product overview: Fluke 2052 Advanced Wire Tracer Kit

Built to Keep You Safe

The Fluke 2052 Advanced Wire Tracer accurately and safely troubleshoots energized and de-energized wires in residential, commercial, and industrial environments up to CAT IV 600 V. This CAT rating offers the highest protection available on any wire tracer. It's designed to protect you from the most dangerous levels of transient overvoltage, spikes up to 8,000 V, that can occur in industrial and utility environments. This is especially important for scenarios you may encounter in environments like industrial plants, factories, and hospitals where critical equipment cannot be taken offline.

Wire Tracing Customized for Your Application

Whether troubleshooting electrical wiring and equipment in residential homes, commercial buildings, or high-voltage utility plants, the Fluke 2052 can find breaks or opens and shorts. Its different modes and functions give you the flexibility to troubleshoot a wide range of electrical wiring and circuitry problems you may encounter on the job.

Four Receiver Tracing Modes

The 2052-R Receiver detects the signal in wires and cables using two methods: passive tracing without the transmitter for non-contact voltage detection and active tracing with the transmitter for all other modes. The receiver's tip sensor can trace wires in corners, tight spaces, and junction boxes.

- "Quick Scan" mode for energized wire detection and visualization on the large color LCD
- "Precision" mode for more precise detection of a wire
- "Breaker" mode for easy breaker and fuse identification based on the highest recorded signal detected from the transmitter
- "Non-Contact Voltage Detection" mode to trace energized wires without the use of the transmitter

Three Transmitter Power Modes

The 2000-T Transmitter works on energized and de-energized circuits up to CAT IV 600 V and features high, low, and loop modes. These modes change the strength of the induced signal and can help provide more accurate results, depending on the circuit you're tracing.

- "High" mode for normal energized and de-energized circuits
- "Low" mode for precision tracing with a low signal to reduce coupling to nearby wires and metal objects
- "Loop" mode for closed loop de-energized circuits

Two Transmitter Output Frequencies

The 2000-T automatically senses whether the system is energized or de-energized and selects a 6 kHz or 33 kHz output frequency.

Eight Receiver Sensitivity Levels

More sensitivity levels mean more flexibility and accuracy when tracing.

Complete Kit

The Fluke 2052 Advanced Wire Tracer Kit conveniently comes with everything required to start tracing wires and circuits. The accessory kit includes test leads, test probes, blade and round outlet adapters, and alligator clips to connect the transmitter to electrical systems. Connecting the transmitter to a bare conductor with the included alligator clips and test leads will always provide the most accurate results. However, in situations where a direct connection to a bare conductor is not available, the included i400 Current Clamp can be used with the "Loop" mode to induce a boosted 6 kHz signal through the insulation. The kit also includes batteries and a hard carrying case.

Specifications: Fluke 2052 Advanced Wire Tracer Kit

General	2052R Receiver	2000T Transmitter	i400 AC Current Clamp
Measurement category	CAT IV 600 V	CAT IV 600 V	CAT IV 600 V, CAT III 1000 V
Operating voltage	600 V AC/DC	600 V AC/DC	1000 V AC
Operating frequency	Energized: 6.25 kHz ttDe-Energized: 32.768 kHz	Energized/Loop: 6.25 kHz ttDe-Energized: 32.768 kHz	N/A
Signal indications	Numeric, bar graph display and audible beep	LEDs and audible beep	N/A
Response time	Tip Sensor (Energized/De-Energized): 500 ms ttNCV: 500 ms ttBaery monitoring: 5 s	Line voltage monitoring: 1 s ttBaery voltage monitoring: 5 s	N/A

Current output of signal (typical)	N/A	Energized circuit: ttHigh mode: 60 mA rms ttLow mode: 30 mA rms ttDe-energized circuit: ttHigh mode: 110 mA rms ttLow mode: 40 mA rms ttLoop mode with test leads: 160 mA rms ttLoop mode with i400 AC Current Clamp: tt385 mA rms	N/A
Signal voltage output (nominal)	N/A	Energized circuit: ttHigh mode: 14 W @ 230 V ac/50 Hz, tt3.33 ku03a9 @ 230 V ac ttLow mode: 4.6 W @ 230 V ac/50 Hz, tt1.5 ku03a9 @ 230 V ac ttDe-energized circuit: ttHigh mode: 31 V RMS, 140 Vp-p, tt0.86 W @ 1 ku03a9 load ttLow mode: 27.5 V RMS, 120 Vp-p, tt0.1 W @ 1 ku03a9 load ttLoop mode with test leads: 32 V RMS, tt140 Vp-p, 0.87 W @ 1 ku03a9 load ttLoop mode with i400 AC Current Clamp: tt31 mV, 0.89 W @ 1 u03a9 load	N/A
Range detection (open air)	Tip Sensor: Energized ttMax distance via air: up to 6.1 m (20 ft) ttPinpointing: approx. 5 cm (1.97 in) ttTip Sensor: De-Energized ttMax distance via air: up to 4.5 m (14.7 ft) ttPinpointing: approx. 5 cm (1.97 in) ttNCV (40 Hz to 400 Hz) ttMax. sensitivity: 90 V up to 2 m ttMin. sensitivity: 600 V up to 1 cm		N/A
Current range	N/A	N/A	400 A
Basic accuracy	N/A	N/A	2 % + 0.06 A tt(45 Hz to 400 Hz)

Display			
Display size	LCD 63 mm (2.5 in)	LEDs	N/A
Display dimensions (W x H)	37 mm x 49 mm (1.45 x 1.93 in)	N/A	N/A
Display Resolution	240 px x 320 px	N/A	N/A
Display type	TFT LCD	LEDs	N/A
Display color	16-bit	Operating mode LEDs: red ttBaery status LEDs: green, yellow, red	N/A
Backlight	Yes	N/A	N/A

Environmental			
Operating temperature	-20 u00b0C to 50 u00b0C (-4 u00b0F to 122 u00b0F)	-20 u00b0C to 50 u00b0C (-4 u00b0F to 122 u00b0F)	-20 u00b0C to 50 u00b0C (-4 u00b0F to 122 u00b0F)
Operating humidity	45%: -20 u00b0C to <10 u00b0C or 40 u00b0C to 50 u00b0C tt(-4 u00b0F to <50 u00b0F or 104 u00b0F to 122 u00b0F) tt95% (non-condensing): 10 u00b0C to <30 u00b0C tt(50 u00b0F to 86 u00b0F) tt75%: 30 u00b0C to <40 u00b0C (86 u00b0F to <104 u00b0F)	45%: -20 u00b0C to <10 u00b0C or 40 u00b0C to 50 u00b0C tt(-4 u00b0F to <50 u00b0F or 104 u00b0F to 122 u00b0F) tt95% (non-condensing): 10 u00b0C to <30 u00b0C tt(50 u00b0F to 86 u00b0F) tt75%: 30 u00b0C to <40 u00b0C (86 u00b0F to <104 u00b0F)	10 u00b0C to <30 u00b0C tt(95 %: 50 u00b0F to <86 u00b0F) tt30 u00b0C to <40 u00b0C tt(75 %: 86 u00b0F to <104 u00b0F) tt40 u00b0C to <50 u00b0C tt(45 %: 104 u00b0F to <122 u00b0F)
Operating altitude	2000 m (6561 ft)	2000 m (6561 ft)	2000 m (6561 ft)
Transient protection	N/A		N/A
Pollution degree	2	2	2
IP rating	IP 40	IP 40	IP 40
Drop test	1 m (3.28 ft)	1 m (3.28 ft)	1 m (3.28 ft)

Mechanical			
Power supply	4 x AA (alkaline)	8 x AA (alkaline)	N/A

Power consumption (typical)	110 mA	High/low mode: 70 mA ttLoop mode with Clamp: 90 mA ttConsumption without signal transmission: 10 mA	N/A
Baery life	Approx. 16 h	High/low mode: approx. 25 h ttLoop mode: approx. 18 h	N/A
Low baery indication	Yes	Yes	N/A
Fuse	N/A	1.6 A, 700 V, fast-acting, ttu00d8 6 x 32 mm, 50 kA interrupt	N/A
Maximum conductor size	N/A	N/A	32 mm (1.26 in)
Dimensions (L x W x H)	Approx. 183 x 75 x 43 mm tt(7.2 x 2.95 x 1.69 in)	Approx. 183 x 93 x 50 mm tt(7.2 x 3.66 x 1.97 in)	Approx. 150 x 70 x 30 mm tt(5.9 x 2.75 x 1.18 in)
Weight	Approx. 0.27 kg (0.6 lb)	Approx. 0.57 kg (1.25 lb)	Approx. 0.114 kg (0.25 lb)

Mechanical	2000ACC Test Lead Accessory Kit
Includes	2x 1 m test leads (red, black), tt1x 7 m test lead (green), tt2x test probes (black), tt2x alligator clips (red, black), tt2x outlet blade adapters (red, black), tt2x outlet round adapters (red, black)
Measurement category	CAT IV 600 V (test leads), CAT II 1000 V (test probes), CAT IV 600 V (alligator clips), ttCAT II 300 V (outlet adapters)
Operating voltage and current	600 V, 10 A max. (red/black leads), 600 V, 10 A max. (green lead), 1000 V, 8 A max. (black probe) tt600 V, 10 A max. (alligator clips), 300 V, 10 A max. (outlet adapters)
Operating temperature	0 u00b0C to 50 u00b0C (32 u00b0F to 122 u00b0F)
Operating humidity	10 u00b0C to <30 u00b0C (95 %: 50 u00b0F to <86 u00b0F), 30 u00b0C to <40 u00b0C (75 %: 86 u00b0F to <104 u00b0F), tt40 u00b0C to <50 u00b0C (45 %: 104 u00b0F to <122 u00b0F)
Storage temperature and humidity	0 u00b0C to 60 u00b0C (32 u00b0F to 140 u00b0F),
Operating altitude	2000 m (6561 ft)
Pollution degree	2
Water and dust resistance	IP 20
Drop proof	1 m (3.28 ft)
Dimensions	Red/black leads: 1 m (3.28 ft), Green lead: 7 m (22.97 ft), Alligator clips: approx. 95 x 45 x 24 mm (3.74 x 1.77 x 0.94 in), ttOutlet adapters: 72 x 18 x 18 mm (2.83 x 0.71 x 0.71 in)
Weight	Approx. 0.4 kg (0.88 lb)

Ordering information



FLUKE-2052

Includes:

- Fluke 2052R Advanced Wire Tracer Receiver
- Fluke 2000T Advanced Wire Tracer Transmitter
- i400 AC Current Clamp
- Fluke 2000ACC Test Lead Accessory Kit for 2052/2062
- Premium hard carrying case
- Batteries
- Quick reference guide

Optional accessories

Fluke i400 AC Current Clamp

Description

Fluke i400 AC current clamps extend the use of digital multimeters. Get a single range 400 A AC clamp in a compact shape.

Fluke TPAK ToolPak™ Magnetic Meter Hanger

Powerful magnetic strap for safe, hands free measurements.

CXT1000 Extreme Hard Case

The CXT1000 is a rugged hard case that allows you to configure the diced foam interior to store, protect, and carry your all your Fluke test tools and accessories.

Fluke. *Keeping your world up and running.®*

Fluke Europe B.V.

P.O. Box 1186
5602 BD Eindhoven
The Netherlands
www.fluke.com/en

©2024 Fluke Corporation. All rights reserved.
Data subject to alteration without notice.
10/2024

For more information call:

In Middle East/Africa
+31 (0)40 267 5100

**Modification of this document is not permitted
without written permission from Fluke Corporation.**